



BE3500PS

3500 WATT GENERATOR



SPECIFICATIONS

3500 WATT INVERTER

- 208CC POWEREASE ENGINE
- 3500 MAX WATT OUTPUT
- 2800 RUNNING WATT OUTPUT
- RECOIL START
- RECEPTACLES:
 - 2 × 120V DUPLEX (20A)
 - 1 × 120V TWISTLOCK (30A)
- LOW OIL SHUTDOWN
- DECIBEL RATING: 7M: 70DB
- RUN TIME PER TANK: 9H @ FULL LOAD
- AUTOMATIC VOLTAGE REGULATOR (AVR)
- THD (TOTAL HARMONIC DISTORTION) 8.0
- CONT. AMPS (120V) 25A
- FUEL TANK CAPACITY: 15 L / 3.9 GAL
- NO WHEEL KIT
- VOLTAGE SELECTOR
- FUEL GAUGE
- CIRCUIT BREAKERS

PART# BE3500PS

SHIPPING

